

# MeasureReady™ M91 FastHall™ Measurement controller




# MeasureReady™ M91 FastHall™ Measurement controller

## A new approach to Hall measurement

The MeasureReady M91 is a revolutionary, all-in-one Hall analysis instrument that delivers significantly higher levels of precision, speed, and convenience to researchers involved in the study of electronic materials.

Featuring Lake Shore's patented\* new FastHall measurement technique, the M91 fundamentally changes the way the Hall effect is measured by eliminating the need to switch the polarity of the applied magnetic field during the measurement. This breakthrough results in faster and more accurate measurements, especially when using high field superconducting magnets or when measuring very low mobility materials.

*\*Protected by US patent numbers 9797965 and 10073151. Other patents pending.*



**Ideal for measuring  
low mobility materials**



### Simpler and more convenient

- All-in-one instrument
- Automatically selects optimal excitation and measurement levels
- Automatically executes measurement steps
- Provides complete Hall analysis
- Easy to use, easy to integrate with existing lab systems



### Makes better measurements, faster

- No need to reverse the magnetic field with FastHall
- Up to 100x faster for low mobility materials
- Improves accuracy by minimizing thermal drift



### Cost effective

- Build a new Hall system or upgrade an existing one
- Add state-of-the-art Hall measurement capability to any lab
- Use with any type of magnet



*MeasureReady M91 FastHall  
measurement controller  
automatically checks  
sample contact quality and  
graphically displays results.*

# MeasureReady™ M91 FastHall™ Measurement controller



Executes a complete Hall measurement sequence:




## A convenient, single instrument

Traditional Hall effect measurement systems (HMS) provide basic electrical measurement instrumentation combined with a switching unit to measure sample resistivity and Hall voltages, but must rely on separate PC-based software to perform pre- and post-measurement calculations in order to ultimately derive the physical parameters that researchers need to know—resistivity, carrier type, carrier concentration, mobility, and Hall coefficient.

The M91 FastHall measurement controller combines all of the necessary HMS functions into a single instrument, automating and optimizing the measurement process, and directly reporting the calculated parameters.

## Typical HMS



**Adding HMS capabilities to any research platform has never been easier!**



# MeasureReady™ M91 FastHall™ Measurement controller

## Better measurements in less time

Lake Shore's patented new FastHall technology eliminates the need to reverse the field, significantly reducing the time to make measurements without reducing measurement quality. In fact, a shorter measurement window lessens the opportunity for sample parameters to drift due to self-heating or ambient temperature change.

A unidirectional field also removes potential sources of measurement bias due field alignment errors, further improving the quality of the result.

With FastHall, any type of magnet can be used. For research platforms with high field superconducting magnets, the elimination of field reversal is especially beneficial.




## Ideal for low mobility materials

Traditional DC field Hall effect measurement is relatively straightforward and reliable for simpler materials with higher mobilities. Measurement difficulty increases and accuracy decreases as carrier mobilities decrease. This is often the case in promising new semiconductor materials such as photovoltaics, thermoelectrics, and organics.

AC field techniques using advanced lock-in amplifiers and longer measurement windows can extract smaller Hall voltage signals and are commonly used today to explore low mobility materials. Extended measurement intervals can also add error from thermal drift effects and results take longer to get—sometimes many hours.

The FastHall technique eliminates both of these issues — it accurately measures even extremely low mobility materials in seconds.



The DC field Hall effect process requires taking voltage measurements with the magnetic field set in one direction, followed by reversal of the field polarity and repetition of the voltage measurements. The type of magnet used and the number of measurement samples needed for satisfactory data impact the overall measurement time.

## Comparison of HMS techniques

	FastHall™	AC field	DC field
Eliminates field reversal	✓	✗ AC field (sinusoidal)	✗
Can be used with permanent magnets	✓ FAST	✗	✓ MANUAL
Can be used with electromagnets	✓ FAST	✓ SLOWER WITH LOWER MOBILITIES	✓ SLOWER WITH LARGE ELECTROMAGNETS
Can be used with superconducting magnets	✓ FASTER THAN DC FIELD	✗	✓ SLOW
Measurement capability	Lower mobility: ~10 <sup>-3</sup> cm <sup>2</sup> /V s and up	Lower mobility: ~10 <sup>-3</sup> cm <sup>2</sup> /V s and up	Higher mobility: ~1 cm <sup>2</sup> /V s and up

*FastHall measurement requires Van der Pauw sample configurations (Hall bar configurations measured with DC field)*

*AC field measurement not currently supported in the M91—contact Lake Shore for more information*

# MeasureReady™ M91 FastHall™ Measurement controller

## Materials

### Solar cells

OPVs, a:Si,  $\mu$ c-Si, CdTe, CuInGaSe (CIGS)

### Organic electronics

OTFTs, Pentacene, Chalcogenides, OLEDs

### Transparent conducting oxides

InSnO (ITO), ZnO, GaZnO, InGaZnO (IGZO)

### III-V semiconductors

InP, InSb, InAs, GaN, GaP, GaSb, AlN based devices, high electron mobility transistors (HEMTs) and heterojunction bipolar transistors

### II-VI semiconductors

CdS, CdSe, ZnS, ZnSe, ZnTe, HgCdTe

### Elemental semiconductors

Ge, Si on insulator devices (SOI), SiC, doped diamond  
SiGe based devices: HBTs and FETs

### Dilute magnetic semiconductors

GaMnAs, MnZnO

### Half-Heusler compounds

TiNiSn, ZrNiSn, GdPtBi

### Topological semi-metals

TaAs, WTe<sub>2</sub>, MoTe<sub>2</sub>

### Topological insulators

Bi<sub>2</sub>Te<sub>3</sub>, Bi<sub>2</sub>Se<sub>3</sub>, Sb<sub>2</sub>Te<sub>3</sub>

### Transition-metal Di-chalcogenides (TMDC)

WS<sub>2</sub>, WSe<sub>2</sub>, MoS<sub>2</sub>, HfS<sub>2</sub>

### Other 2D materials

BN, graphene structures

### Other conducting materials

Metal oxides  
Organic and inorganic conductors

### High temperature superconductors

## Key features


- Hall analysis including calculation of derived parameters for van der Pauw and Hall bar samples
- FastHall technology eliminates the need for magnetic field reversal when measuring van der Pauw samples—extends mobility range down to 0.001 cm<sup>2</sup>/V s
- Traditional DC field Hall measurement mode for both Hall bar and van der Pauw samples
- Automated operation for maximum convenience—includes automatic optimization of excitation values and measurement range
- Manual step-by-step mode for full parameter control
- High-resistance option—enables measurement of samples to 200 GΩ
- Outputs all measured values plus derived parameters
- 1-year calibration
- 3-year standard warranty



## A cost effective way to build a new Hall system or upgrade an existing one

A few simple connections and you're ready to begin analyzing your samples. Whether you choose to use a simple benchtop holder and magnet, a magnet-equipped probe station, an electromagnet platform, or a more specialized apparatus, the M91 makes it easy to bring state-of-the-art Hall measurement capability to your lab.

Lake Shore's versatile MeasureLINK-MCS software, included with each M91, gives you a simple way to customize, start, and step-through your measurement sequences, as well as chart, log and organize the results. MeasureLINK also enables automated control of field, management of sample temperature, and coordinated integration with other instrumentation and measurement protocols. With MeasureLINK, the M91 FastHall measurement controller becomes an even more powerful component to support your advanced semiconductor research.



# MeasureReady™ M91 FastHall™ Measurement controller

*The MeasureReady M91 FastHall measurement controller offers the ultimate in HMS speed, convenience, and accuracy*

## Measurement applications

The M91 is capable of running a wide array of Hall analysis functions including:

### Hall voltage

- Resolution = 1  $\mu\text{V}$
- Noise = 0.1  $\mu\text{V}$  (RMS), averaged over 1 power line cycle

### Resistance/resistivity (four-contact in-line probe and van der Pauw)

- Calculated by instrument
- Resistance range 10 m $\Omega$  to 10 M $\Omega$  standard
- Up to 200 G $\Omega$  with high-resistance option

### Magnetoresistance

- System provides field control to measure resistance as a function of magnetic field

### Hall coefficient

- Calculated by instrument
- Derived from Hall voltage, magnetic field, and current

### Hall mobility

- Calculated by instrument
- $10^{-3}$  to  $10^6$  cm<sup>2</sup>/V s

### Anomalous Hall effect (AHE)

- System provides field control to measure Hall voltage as a function of magnetic field

### Carrier type/concentration/density

- Sheet or volume carrier concentration calculated
- Typical sheet carrier density  $\leq 10^{17}$  cm<sup>-2</sup> (carrier density depends on measurement parameters)

## More science, less time

The M91 is extremely fast, reducing analysis time in some cases by 100x. Most commonly measured materials can be analyzed in a few seconds. Even extreme high resistance (up to 200 G $\Omega$ ) or low mobility ( $\sim 0.001$  cm<sup>2</sup>/V s) samples can generally be analyzed in under 2 min. With other HMS techniques, this could take hours to complete.

The M91 encourages rapid initial assessments of materials to determine if further study or greater accuracy is warranted. Spend less time waiting and more time doing real science.

## Get all the data

Analysis of low mobility or high resistance materials faces challenges due to very low signal-to-noise ratios. Inaccurate measurements are likely unless sophisticated techniques and/or larger measurement samples are used.

With some HMS solutions, the researcher often has little chance to double check the intermediate results of the analysis, and can therefore be easily misled as to the validity of the reported results.

The M91 collects all the data. In addition to performing the complete Hall analysis and outputting the usual measured and derived mobility values, the M91 can also generate detailed reports including all of the supporting intermediate data, so the researcher can readily confirm the integrity of the final results.

The image displays several overlapping report windows from the MeasureReady M91 FastHall measurement controller. The reports include:

- Contact Check Results Summary:** Shows contact pair information, R Squared Value, Contact Pair Fail, Linear Fit - Offset, and Linear Fit - Slope.
- Results Summary:** Provides Average Resistivity, Resistivity Standard Error, Start Time, and End Time.
- Setup Information:** Details Excitation Type, Excitation Value, Excitation Range, Measurement Range, Compliance Limit, Number of Samples to Average, and Blanking Time.
- Resistivity Report:** Lists Excitation Type, Excitation Value, Excitation Range, Measurement Range, Compliance Limit, Number of Samples to Average, and Blanking Time.
- FastHall Results Summary:** Contains Average Hall Voltage, Hall Voltage Standard Error, Average Hall Coefficient, Hall Coefficient Standard Error, Average Carrier Concentration, Carrier Concentration Standard Error, Carrier Type, p-type count, n-type count, Start Time, End Time, Measurement Duration (ms), Source Is Compliance (true = false), Measurement Is Current Overload (true = false), Measurement Is Voltage Overload (true = false), and Actual Blanking Time (ms).

# MeasureReady™ M91 FastHall™ Measurement controller


## Built for science, designed for people

The M91 is a powerful research instrument that incorporates Lake Shore's decades of experience in Hall effect measurement. It's also really easy to work with.

## Easy to get started

- Begin using the M91 right out of the box with the included MeasureLINK-MCS application software
- Install MeasureLINK on your laptop and easily enter measurement parameters
- MeasureLINK enables you to easily initiate Hall measurement sequences and view graphical results
- Measurement sequences can be readily customized and adapted to your research needs


## MeasureLINK™




## Easy to use

- Onboard touchscreen UI displays measurement process steps as they execute in real time, and provides quick access to view high-level measurement results
- Ergonomically designed package features TiltView™ display for best visibility, whether on a bench or mounted in a rack

## See and operate more easily with TiltView™



## Maximum angle of operation comparison




## Easy to integrate

- Simple SCPI command interface
- MeasureLINK software facilitates integration with third party instruments and software
- Hardware digital and analog I/O for OEM system interfaces

# MeasureReady™ M91 FastHall™ Measurement controller

## MeasureReady™ M91 rear panel



- ① Triaxial sample connectors
- ② Analog input
- ③ Analog output
- ④ Signal RTN
- ⑤ Digital output
- ⑥ Digital input
- ⑦ WLAN antenna
- ⑧ RJ-45 Ethernet interface
- ⑨ USB communications interface
- ⑩ USB thumb drive interface
- ⑪ Line input assembly
- ⑫ Chassis ground connection

## Options

### **GPIB-LAN-CONVERT** GPIB to LAN converter

For applications requiring IEEE-488 communications, this converter plugs into the instrument's LAN port and creates a GPIB-compatible interface. Note that network timing may be affected when using parallel to serial converters. Delays vary with the amount of data transferred and the converter's activity as messages are received.



## Be future-ready with Measure Ready

With free online firmware updates, your instrument can always have the most current capabilities. And as Lake Shore introduces new options in the future, you can purchase and download them to your instrument. This allows the controller to grow as your measurement needs evolve.



# MeasureReady™ M91 FastHall™ Measurement controller

## M91 specifications

### Hall measurement

FastHall™ method (no physical field reversal) — van der Pauw samples  
Traditional DC method — Hall bar and van der Pauw samples

### Derived parameters

Hall coefficient, Hall mobility, resistivity, carrier concentration

### Sheet resistance

**Lowest range:** 10 mΩ

**Highest range:** up to 10 MΩ

**Highest range with M9-ADD-HR high resistance option:** up to 200 GΩ

### Hall mobility range

0.001 to 10<sup>6</sup> cm<sup>2</sup>/V s

### Programmable limits

**I out:** compliance voltage; **V out:** current limit

**Positive output:** ±5% of setting (when setting is >10% of its full-scale range)

**Negative output:** ±5% of setting (when setting is >10% of its full-scale range)

**Programming resolution current limit:** 0.1% of full-scale current range (auto selected)

**Programming resolution voltage limit:** 10 mV

### Analog input

**Analog input raw signal accuracy:** ±300 mV of reading

**Raw analog input voltage range:** ±11 V

**Safe input voltage range:** ±15 V

**Compliance voltage (typical):** ≤10 V

**Current limit (typical):** ≤0.1 A

### Analog output

**Analog output raw signal accuracy:** ±300 mV of setting

**Raw analog output voltage range:** ±11 V rails, ±15 V max during overload

### Digital input

**Number of independent inputs:** 4

**Input isolation:** Optical

**Maximum low-level input voltage:** 1 V

**Minimum high-level input voltage:** 4 V

**Safe input voltage range:** -5 V to 32 V

### Digital output

**Number of independent outputs:** 4

**Relay type:** Solid state

**Digital output relay max current:** 1.5 A

**Digital output relay max voltage:** 32 V

### Rear panel test connectors

Sample connections: 6 individual 3-lug socket triaxial connectors

Analog input BNC

Analog output BNC

10-pin Phoenix connector for digital output

10-pin Phoenix connector for digital input

2-pin Phoenix connector for signal return

### Front panel

**Display:** 5 in capacitive touch, color TFT-LCD WVGA (800 × 480) with LED backlight

### Interface

#### USB host

Type: USB 3.0, mass storage class (MSC) device  
Function: Firmware updates, flash drive support  
Location: Rear panel  
Connector: USB Type-C™

#### USB device

Type: USB 2.0  
Function: Emulates a standard RS-232 serial port  
Protocol: Standard commands for programmable instruments (SCPI)  
Baud rate: 921,600  
Connector: USB Type-B  
Software support: LabVIEW™ and IVI.NET drivers (see www.lakeshore.com)

#### Ethernet

Function: TCP/IP command and control, mobile app  
Application layer protocol: Standard commands for programmable instruments (SCPI)  
Connector: RJ-45  
Speed: 1 Gb/s  
Software support: LabVIEW™ and IVI.NET drivers (see www.lakeshore.com)

#### Wi-Fi

Type: 802.11 b/g/n  
Function: TCP/IP command and control, mobile app  
Application layer protocol: Standard commands for programmable instruments (SCPI)  
Antenna: External, coaxial  
Software support: LabVIEW™ and IVI.NET drivers (see www.lakeshore.com)

#### Wireless personal area network (WPAN)

Function: Short-range, wireless interconnection  
Antenna: External, coaxial

### General

**Operating conditions:** 23°C ±5°C at rated accuracy;  
10°C to 35°C at reduced accuracy,  
<70% RH non-condensing

**Instrument maximum field exposure:** Operational limit <10 mT DC, 1 mT RMS;  
Guaranteed performance <2 mT RMS

**Power requirement:** 100 V to 240 V (universal input),  
50 to 60 Hz, 30 VA

**Size:** 216 mm W × 87 mm H × 369 mm D  
(8.5 in × 3.4 in × 14.5 in), half rack

**Weight:** 3.2 kg

**Approval:** CE mark

**FCC ID (wireless radio):** TFB-TIW11-01

**Warm-up time:** 30 min

**Power consumption:** 35 W maximum

# MeasureReady™ M91 FastHall™ Measurement controller

## Measurement performance

		Voltage measurement range					
		1 mV	10 mV	100 mV	1 V	10 V	
Current excitation range	1 $\mu$ A	Resistance at maximum voltage	1 k $\Omega$	10 k $\Omega$	100 k $\Omega$	1 M $\Omega$	10 M $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.2%	0.06%	0.06%	**	**
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	0.001%	**	**
	10 $\mu$ A	Resistance at maximum voltage	100 $\Omega$	1 k $\Omega$	10 k $\Omega$	100 k $\Omega$	1 M $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.2%	0.06%	0.06%	0.06%	**
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	0.001%	0.001%	**
	100 $\mu$ A	Resistance at maximum voltage	10 $\Omega$	100 $\Omega$	1 k $\Omega$	10 k $\Omega$	100 k $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.2%	0.2%	0.06%	0.06%	0.06%
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	0.001%	0.001%	0.5%
	1 mA	Resistance at maximum voltage	1 $\Omega$	10 $\Omega$	100 $\Omega$	1 k $\Omega$	10 k $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.2%	0.2%	0.2%	0.06%	0.06%
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	0.001%	0.001%	0.5%
	10 mA	Resistance at maximum voltage	0.1 $\Omega$	1 $\Omega$	10 $\Omega$	100 $\Omega$	1 k $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.5%	0.2%	0.2%	0.2%	0.2%
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	0.001%	0.001%	0.5%
	100 mA	Resistance at maximum voltage	0.01 $\Omega$	0.1 $\Omega$	1 $\Omega$	10 $\Omega$	100 $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.5%	0.2%	0.2%	0.2%	**
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	0.001%	0.001%	**

\*\* Range available, not specified

<sup>1</sup> Calibration temperature is the ambient temperature during factor calibration; typically, 23 °C; reported by the instrument  
All accuracies based on current reversal measurements.

## With high resistance option only

		Current measurement range				
		10 nA	100 $\mu$ A	10 mA	100 mA	
Voltage excitation range	10 mV	Resistance at maximum current	1 M $\Omega$	1 k $\Omega$	1 $\Omega$	0.1 $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.5%	**	**	**
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	**	**	**
	100 mV	Resistance at maximum current	10 M $\Omega$	10 k $\Omega$	10 $\Omega$	1 $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.5%	**	**	**
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	**	**	**
	1 V	Resistance at maximum current	100 M $\Omega$	100 k $\Omega$	100 $\Omega$	10 $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.8%	0.5%	**	**
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	**	**
	10 V	Resistance at maximum current	1 G $\Omega$	1 M $\Omega$	1 k $\Omega$	100 $\Omega$
		Accuracy (1 year) calibration temperature °C $\pm$ 5 °C $\pm$ % reading <sup>1</sup>	0.5%	0.5%	**	**
		Temperature coefficient/°C 10 °C to 35 °C $\leq$ 65% RH non-condensing $\pm$ % reading (typical)	0.001%	0.001%	**	**

\*\* Range available, not specified

<sup>1</sup> Calibration temperature is the ambient temperature during factor calibration; typically, 23 °C; reported by the instrument  
All accuracies based on voltage reversal measurements.

# MeasureReady™ M91 FastHall™ Measurement controller

Current measurement range	DC Accuracy (1 year) calibration temperature °C ± 5 °C ± % reading <sup>1</sup>
10 mA	0.3%
100 mA	0.3%

<sup>1</sup> Calibration temperature is the ambient temperature during factor calibration; typically, 23 °C; reported by the instrument

## Voltage and current excitation specifications

Voltage excitation range	Programming resolution (0.001%)	Temperature coefficient/°C 10 °C to 35 °C ± (% setting + offset), typical
10 mV	100 nV	0.06% + 4 µV
100 mV	1 µV	0.005% + 4 µV
1 V	10 µV	0.0004% + 20 µV
10 V	100 µV	0.0004% + 200 µV
Current excitation range	Programming resolution (0.001%)	Temperature coefficient/°C 10 °C to 35 °C ± (% setting + offset), typical
1 µA	10 pA	0.002% + 9 pA
10 µA	100 pA	0.0004% + 20 pA
100 µA	1 nA	0.0004% + 90 pA
1 mA	10 nA	0.0004% + 40 pA
10 mA	100 nA	0.0004% + 4 nA
100 mA	1 µA	0.0004% + 40 nA

## Voltage and current measurement specifications

Voltage measurement range	Temperature coefficient/°C 10 °C to 35 °C ± offset (typical)
1 mV	50 nV
10 mV	50 nV
100 mV	200 nV
1 V	2 µV
10 V	20 µV
Current measurement range	Temperature coefficient/°C 10 °C to 35 °C ± offset (typical)
10 nA	2 pA
10 µA	7 pA
10 mA	7 nA
100 mA	70 nA

## Ordering information

<b>M91</b>	MeasureReady™ M91 FastHall™ controller with accessory kit (M91-ACC-KIT)
<b>M91-HR</b>	MeasureReady M91 FastHall controller with high resistance option and accessory kit (M91-ACC-KIT)
<b>M91-ACC-KIT</b>	MeasureReady M91 accessory kit: USB-A to USB-C adapter, USB-A male to USB-B male cable, terminal connectors for digital I/O, terminal connectors for chassis ground, line power cord, wireless antenna, and quick-start guide
<b>M9-ADD-HR</b>	M91 firmware upgrade to include high resistance samples to 200 GΩ
<b>GPIB-LAN-CONVERT</b>	GPIB to LAN converter; enables GPIB communications and control of a LAN instrument; GPIB data transfer rates not guaranteed and will be limited by LAN transfer rates
<b>RMX-FULL</b>	Full-rack mount kit
<b>RMX-HALF</b>	Half-rack mount kit
<b>813-100</b>	Low noise triaxial cable, 3-slot, 1 m (3 ft)
<b>843-062</b>	Low noise triaxial cable, 3-slot, 3.7 m (12 ft)
<b>P12379</b>	BNC female to triaxial adapter, TRB male, 3 lug, isolated, 50 Ω

# MeasureReady™ M91 FastHall™ Measurement controller

Copyright © Lake Shore Cryotronics, Inc. All rights reserved. Specifications are subject to change.

Lake Shore Cryotronics, the Lake Shore logo, the square graph logomark, and Cernox are registered trademarks of Lake Shore Cryotronics, Inc.

All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.

101519

## Questions? Answers?

Visit <http://forums.lakeshore.com/> and become part of the conversation!

